



PROTON

## JSC "PROTON"

302040, Russia, Orel, Leskova 19 str.

Phone/fax: +7(4862) 49-85-34, +7(4862) 41-44-03

E-mail: [export1@proton-orel.ru](mailto:export1@proton-orel.ru), [www.proton-orel.ru](http://www.proton-orel.ru)

### LED CROSSING LIGHT P.2.1-CPA-F-1

#### Description

LED crossing light consists of two emitters displaying walking man image of green lighting and standing man image of red lighting. Walking and standing man images combined with two-digit countdown panel of corresponding lighting colours. Countdown panel displays the time left to red or green lighting. The time of green signal displayed by green figures lighting, the time of red signal displayed by red figures lighting.

Crossing light board supplied with intellectual option, automatically fit into time modes of road controller.

Works with any type of road controller.

According to customer`s demand the crossing light can be accomplished by additional contour screen.

Combined application of crossing light and countdown panel enables to decrease the amount of road accidents and especially accidents with pedestrians.

#### Technical characteristics

Diameter of signal exit aperture		<b>200×200 mm</b>
Axial luminous intensity of signals	Red	<b>not less 50 cd</b>
	Green	<b>not less 50 cd</b>
Power consumption	Red	<b>not more 11 W</b>
	Green	<b>not more 9 W</b>
Amount of countdown panel digit orders		<b>2</b>
Maximum counting time of countdown panel		<b>99 sec</b>
Signal radiating frequency		<b>(2300 ±15%) Hz</b>
Sound pressure level		<b>not less 90 dBA</b>
Supply voltage		<b>220 V±15% of road controller</b>
Working temperature range		<b>from - 60°C to +60°C</b>
Dimension		<b>not more 515x314x100 mm</b>
Warranty		<b>5 years</b>
Durability		<b>not less 12 years</b>

#### Outward appearance

